

# AFR-200

RX fiber receiver



## Features:

- ▶ Optical loss indicator

## Specifications:

|               |   |
|---------------|---|
| RX section    |   |
| Bandwidth     | 150-1000MHz                                 |
| RF output     | 2xBNC 50 ohms                               |
| Optical input | Neutrik Opticalcon,<br>1310nm, monomode/APC |
| Supply        | AC 110-220V                                 |
| Dimension     | 435x250x43mm                                |
| Weight        | 3,1kg                                       |

The AFR-200 allows to remote two RX antennas over two monomode fibers. Specially made electro-optical components are used in this equipment. This device is used with one AFB-250. Two indicators « OPTICAL IN » shows if loss on incoming optical signals occurred (from AFB-250). Leds will blink if loss is between 3 and 6dB. Beyond 6 dB leds turn off.

As with other RF equipments some rules applies in order to get the best from this equipment. Feel free to contact us,we'll do our best to help on your projects.

More informations on [www.bs-rf.com](http://www.bs-rf.com) or contact us at [contact@bs-rf.com](mailto:contact@bs-rf.com)

BSRF SAS - 31 boulevard Anatole France 93200 Saint Denis FRANCE

